

# Double-well potentials in current qubits

Mun Dae Kim, Dongkwan Shin, and Jongbae Hong  
*School of Physics, Seoul National University, Seoul 151-747, Korea*  
 (Dated: February 2, 2008)

The effective potentials of the rf-SQUID and three-Josephson junction loop with a penetrating external magnetic flux are studied. Using the periodic boundary condition for the phase evolution of the wave function of Cooper pairs, we obtain new periodic potentials with cusp barriers in contrast with the usual smooth double-well potential. The tunneling through the cusp barrier becomes dominant for a parameter regime where the self inductance of the superconducting loop and the Josephson coupling energy are large. Calculating the tunneling frequency we see that the cusp potential may offer a more efficient qubit.

PACS numbers: 85.25.Dq, 03.67.Lx, 74.50.+r

## I. INTRODUCTION

The rf-SQUID has attracted great attention in connection with the study of quantum two-level systems<sup>1</sup>. In particular it has offered prospects for macroscopic quantum phenomena, such as quantum tunneling and quantum coherence between two quantum states<sup>2</sup>. A frequently appearing structure is the well-known double-well potential with a smooth barrier in some parameter regime. Surprisingly, however, the inspection into the rf-SQUID with precise boundary conditions has not been achieved.

A periodic boundary condition can be obtained by a gauge invariance and the phase evolution by the wave vector of Cooper pairs which is identical with the fluxoid quantization condition. Using this boundary condition, we can obtain the effective potential of an rf-SQUID and three-Josephson junction loop which consist of the energy of moving Cooper pairs and the Josephson coupling energy. The external flux induces a persistent current of Cooper pairs in superconducting loop. When the self inductance of the superconducting loop and the Josephson coupling energy are large, the total flux, sum of the external flux and induced flux, become quantized, while the fluxoid quantization condition is always satisfied.

Considering the energy of Cooper pairs, the effective potential of the system shows a new periodic structure consisting of cusp and smooth barriers. In one extreme, the tunneling through smooth-barrier potential is dominant, which is the usual case<sup>1,2,3,4,5,6</sup>, while, in the other extreme, the cusp barrier potential is more appropriate in tunneling phenomena. Both may be used as a qubit in quantum computing<sup>7,8</sup>. We compare the tunneling rates for the usual smooth-barrier potential and the cusp-barrier potential and show that the latter may offer more effective qubit.

## II. RF-SQUID

We first consider an rf-SQUID shown in Fig. 1 (a). We derive the effective potential of the system showing double-well shapes with both smooth and cusp barriers.

The current through the Josephson junction in Fig. 1 (a) is written as

$$I = -I_c \sin \phi + \frac{V}{R} + C\dot{V}, \quad (1)$$

where  $\phi$  is the superconducting phase difference across the Josephson junction and  $I_c$ ,  $R$ , and  $C$  are critical current, resistance, and capacitance, respectively. Using the relation,  $I = (\Phi_t - \Phi_{\text{ext}})/L_s$ , and the Josephson voltage-phase relation,  $V = -(\Phi_0/2\pi)\dot{\phi}$ , Eq. (1) becomes

$$\Phi_t = \Phi_{\text{ext}} - L_s I_c \sin \phi - L_s \frac{\Phi_0}{2\pi} \left( \frac{\dot{\phi}}{R} + C\ddot{\phi} \right). \quad (2)$$

Here  $\Phi_t$  is the total flux,  $\Phi_{\text{ext}}$  the external flux,  $\Phi_{\text{ind}} = L_s I$  the induced flux,  $L_s$  the self inductance of the superconducting loop, and  $\Phi_0 = h/2e$  the unit flux quantum. When  $L_s I_c / \Phi_0 \ll 1$ , one can use the approximation  $\phi \approx 2\pi\Phi_t / \Phi_0$  in Eq. (2), which results in the usual smooth double-well potential<sup>3</sup>.

The fluxoid quantization condition for a thin superconducting loop<sup>9</sup>,

$$-\Phi_t + (m_c/q_c) \oint \vec{v}_c \cdot d\vec{l} = n\Phi_0 \quad (3)$$




FIG. 1: (a) rf-SQUID and (b) three-Josephson junction loop with the Josephson coupling energy  $E_J$ 's and the wave vector of Cooper pairs  $k$ .

with  $q_c = 2e$ ,  $m_c = 2m_e$ , and the average velocity of Cooper pairs  $\bar{v}_c$ , can be represented as the periodic boundary condition,

$$k_n l = 2\pi n + 2\pi f_t, \quad (4)$$

determining the wave vector at a quantum state  $n$ , where  $k_n$  is the wave vector of the Cooper pairs,  $l$  the circumference of the loop, and  $f_t \equiv \Phi_t/\Phi_0$ . Here,  $k_n l$  is the phase accumulated along the circumference of the loop<sup>10</sup>. For a rf-SQUID in Fig. 1 (a) the boundary condition with the phase difference across the Josephson junction  $\phi$  becomes

$$k_n l = 2\pi n + 2\pi f_t - \phi. \quad (5)$$

The current, on the other hand, is given by  $I = -(n_c A q_c / m_c) \hbar k_n$ , where  $n_c$  is the Cooper pair density,  $A$  the cross section, and the induced flux  $\Phi_{\text{ind}} = L_s I$  becomes

$$\frac{\Phi_{\text{ind}}}{\Phi_0} = -\frac{\gamma l}{2\pi} k_n, \quad (6)$$

where  $\gamma \equiv (q_c^2 n_c A / l m_c) L_s$ . Combining the expression for the total flux,

$$f_t = f + \frac{L_s I}{\Phi_0}, \quad (7)$$

with Eq. (5), the wave vector is written as

$$(1 + \gamma) k_n l = 2\pi n + 2\pi f - \phi, \quad (8)$$

where  $f \equiv \Phi_{\text{ext}}/\Phi_0$ .

Neglecting the dissipative term originating from the quasi-particle tunneling through the junction, Eq. (1) becomes

$$-(n_c A q_c / m_c) \hbar k_n = -I_c \sin \phi - C(\Phi_0 / 2\pi) \ddot{\phi}. \quad (9)$$

With the representation for  $k_n$  in Eq. (8) we get

$$\left(\frac{\Phi_0}{2\pi}\right)^2 C \ddot{\phi} = \frac{\epsilon_0}{(1 + \gamma)\pi} \left(n + f - \frac{\phi}{2\pi}\right) - E_J \sin \phi, \quad (10)$$

where  $E_J = I_c \Phi_0 / 2\pi$  is the Josephson coupling energy and  $\epsilon_0 \equiv 2\pi^2 \hbar^2 n_c A / m_c l$ . Eq. (10) describes the motion of a particle with kinetic energy  $E_C = Q^2 / 2C$  with  $Q = C(\Phi_0 / 2\pi) \dot{\phi}$  in an effective potential  $U_{\text{eff}}(\phi)$ ,

$$U_{\text{eff}}(\phi) = E_n + E_J(1 - \cos \phi), \quad (11)$$

where

$$E_n = \frac{\epsilon_0}{1 + \gamma} \left(n + f - \frac{\phi}{2\pi}\right)^2. \quad (12)$$

The meaning of  $E_n$  can be understood more clearly when we represent  $E_n$  as  $E_n = (1 + \gamma)E_{\text{kin}}$  using Eq. (8), where  $E_{\text{kin}} = (\hbar^2 k_n^2 / 2m_c) n_c A l$  is the kinetic energy of Cooper pairs. Since the induced energy of the loop can be represented as  $E_{\text{ind}} = (1/2) L_s I^2 = \gamma E_{\text{kin}}$ , we can see

that  $E_n$  is the sum of the kinetic energy and the induced energy<sup>11,12</sup>, i.e.,  $E_n = E_{\text{kin}} + E_{\text{ind}}$ . If we introduce the kinetic inductance  $L_k \equiv m_c l / A n_c q_c^2$ , the kinetic energy becomes  $E_{\text{kin}} = (1/2) L_k I^2$  and the parameter  $\epsilon_0$  in Eq. (10) is represented by  $\epsilon_0 = \Phi_0^2 / 2L_k$ . If we introduce the energy scale  $E_K \equiv \Phi_0^2 / 2L_k = \epsilon_0$  and  $E_L \equiv \Phi_0^2 / 2L_s$ , the parameter  $\gamma$  becomes

$$\gamma = \frac{L_s}{L_k} = \frac{E_K}{E_L} \quad (13)$$

and the energy  $E_n$  in Eq. (12) can be rewritten as

$$E_n = \frac{E_K}{1 + \gamma} \left(n + f - \frac{\phi}{2\pi}\right)^2. \quad (14)$$

The similar expression was obtained for a superconducting loop without Josephson junction<sup>13</sup>.

The number of excess Cooper pair charges on Josephson junction  $\hat{N}_c \equiv \hat{Q}/q_c$  is conjugate to the phase difference  $\hat{\phi}$  and the commutation relation  $[\hat{\phi}, \hat{N}_c] = i$  gives the quantum phase fluctuations of the junction. The Hamiltonian  $\hat{H} = \hat{P}^2 / 2M + U_{\text{eff}}(\hat{\phi})$  describes the dynamics of the phase difference, where  $\hat{P} \equiv \hat{N}_c \hbar = -i\hbar \partial / \partial \hat{\phi}$  and




FIG. 2: Lowest energy giving effective potential (solid line) in units of  $E_J$  for  $f=0.49$  as a function of Josephson phase for (a)  $\eta=10$  and (b)  $\eta=5$ . The dotted lines represent the Josephson coupling energy.

$M = (\Phi_0/2\pi)^2 C$ . The charging energy  $E_C$  causes quantum tunneling between two wells in the potential  $U_{\text{eff}}(\phi)$  of the rf-SQUID and the following three-Josephson junction loop.

The double-well structures shown in Fig. 2 are given by taking the lowest energy for the quantum states  $n = -1, 0$ , and  $1$  for the effective potential  $U_{\text{eff}}(\phi)$ . The shape of the effective potential is determined by the parameter  $\eta$  defined by

$$\eta \equiv \frac{E_K}{(1+\gamma)E_J}. \quad (15)$$

For large  $\gamma$ , the value of  $\eta$  can be determined by two parameters  $L_s$  and  $E_J$ . We calculate the value of the parameter  $\gamma$  to obtain  $\gamma \approx 600$  for the parameters of the rf-SQUID of Ref. [4]. At much low temperature  $T \sim O(10\text{mK})$ , we roughly estimate the Cooper pair density in a pure metal  $n_c \approx n/2^9$  with the conduction electron density  $n$ . Even if we consider the effect reducing the Cooper pair density such as band structure of the materials, finite temperature, and so on, we expect that the value of  $\gamma$  is still large such that  $\gamma \gg 1$ . In this case the parameter  $\eta$  is approximately represented as follows,

$$\eta \approx \frac{E_L}{E_J} = \frac{\Phi_0^2}{2L_s E_J} = \frac{\pi \Phi_0}{L_s I_c}, \quad (16)$$

where  $E_J = I_c \Phi_0/2\pi$  with critical current of the Josephson junction  $I_c$ . We obtain that  $\eta \approx 8.5$  for the rf-SQUID<sup>4</sup>.

For the value of  $\eta = 10$ , we can see the double-well structure in Fig. 2 (a) with a smooth barrier centered at  $\phi/2\pi = 0.5$  for  $\Phi_{\text{ext}}/\Phi_0=0.49$ . The usual double-well structure with a smooth barrier corresponds to this one. The left (right) well corresponds to the diamagnetic (paramagnetic) current state. Thus the total flux,  $\Phi_t = \Phi_{\text{ext}} + \Phi_{\text{ind}}$ , for the state at left (right) well approaches  $0(\Phi_0)$  as the self inductance becomes large. For a smaller  $\eta$ , however, a new double-well potential emerges around the cusp as shown in Fig. 2 (b). The high cusp barrier shrinks while the low smooth barrier grows up as  $\eta$  decreases. Thus we get two wells separated by a cusp barrier. The state of current at right (left) well is diamagnetic (paramagnetic).

At the local minima of  $U_{\text{eff}}(\phi)$ , the condition  $\partial U_{\text{eff}}(\phi)/\partial \phi = 0$  gives  $-(n_c A \hbar^2/m_c)k_n + E_J \sin \phi = 0$  and the current relation becomes

$$-\frac{n_c A q_c}{m_c} \hbar k_n + I_c \sin \phi = 0. \quad (17)$$

Actually Eq. (7) is also a current relation, i.e.,  $I = (\Phi_t - \Phi_{\text{ext}})/L_s$ . If one consider both  $\Phi_t$  and  $I$  as independent dynamic variables while  $\Phi_{\text{ext}}$  is a control variable and minimize the energy of the system with respect to the variable  $\Phi_t$ , the current relation, Eq. (7), can be obtained<sup>11,12</sup>. Now the remaining dynamic variables are  $\phi$  and  $I$  or equivalently  $k_n$ . The current relation, Eq. (17), is obtained by minimizing the total energy with respect to the variable  $\phi$ . This current relation warrants the validity of our effective potential.




FIG. 3: The effective potential of three-Josephson junction loop in  $(\phi_a, \phi_b)$  plane, where  $E_{J3}/E_J=0.8$ ,  $f=0.495$ , and  $\eta=1000$ . We set  $\phi_c/2\pi=f/3$ .

### III. THREE-JOSEPHSON JUNCTION LOOP

Recently the superconducting loop with three-Josephson junctions of Fig. 1 (b) has been proposed as an efficient qubit<sup>5</sup>. The periodic boundary condition similar to Eq. (8) is written as

$$(1+\gamma)k_n l = 2\pi n + 2\pi f - \phi_1 - \phi_2 - \phi_3. \quad (18)$$

The effective potential  $U_{\text{eff}}(\phi_1, \phi_2, \phi_3)$  for this qubit is given by

$$U_{\text{eff}}(\phi_1, \phi_2, \phi_3) = E_n + E_J(1 - \cos \phi_1) + E_J(1 - \cos \phi_2) + E_{J3}(1 - \cos \phi_3), \quad (19)$$

where

$$E_n = \frac{E_K}{1+\gamma} \left( n + f - \frac{\phi_1 + \phi_2 + \phi_3}{2\pi} \right)^2. \quad (20)$$

Here we introduced the rotated coordinates  $(\phi_a, \phi_b, \phi_c)$  such that  $\phi_a \equiv (1/2)(\phi_1 + \phi_2)$ ,  $\phi_b \equiv (-1/2)(\phi_1 - \phi_2)$ , and  $\phi_c \equiv (1/3)(\phi_1 + \phi_2 + \phi_3)$ . Then the effective potential of this qubit is written as,

$$U_{\text{eff}} = \frac{E_K}{1+\gamma} \left( n + f - \frac{3}{2\pi} \phi_c \right)^2 + 2E_J(1 - \cos \phi_a \cos \phi_b) + E_{J3}[1 - \cos(3\phi_c - 2\phi_a)]. \quad (21)$$

Fig. 3 shows the effective potential at  $\phi_c/2\pi = f/3$ , where we can see that the value of  $\phi_b$  is strongly localized around  $\phi_b = n\pi$  since the barrier between  $Q$  and




FIG. 4: Contour plots for the effective potential of three-Josephson junction qubit with (a)  $\eta=50$  and (b)  $\eta=2$  when  $f=0.495$  and  $\phi_b=0$ . A, B, C, and D denote the ground states at the local potential minima. The lines  $\phi_c \approx 0$  in (a) and (b) represent the cusp barrier. The potential in (c) is drawn along the line connecting the points A and C for  $\eta = 50$ , while the potential in (d) is for the points A and D for  $\eta = 2$ .

$R$  is much higher than that between  $P$  and  $Q$ . This means that the phase differences at the potential minima in identical Josephson junctions are  $2\pi n$ . For  $\phi_b = 0$  the effective potential is shown in Fig. 4. The barriers between A and C as well as between B and D are smooth, as can be seen in Fig. 4 (c). The two current states at A and C correspond to the qubit states of Ref. [5], where  $\eta$  is so large that the cusp barrier is high enough for tunneling across the barrier to be neglected. The cusp barrier between A and D shrinks while the smooth barrier grows as  $\eta$  decreases. In Fig. 4 (d), thus, we can see the cusp barrier between A and D. The tunneling through this cusp barrier becomes dominant as  $\eta$  becomes small.

The current in the loop is given by  $I = -I_c \sin \phi_a$ . Thus the current states at A and B (C and D) are in a paramagnetic (diamagnetic) current state. The values of  $\phi_a$  and  $\phi_c$  at potential minima can be obtained through the current relations,  $\partial U_{\text{eff}}/\partial \phi_i = 0$  which give

$$\frac{E_K}{(1+\gamma)\pi} \left( n + f - \frac{\phi_1 + \phi_2 + \phi_3}{2\pi} \right) = E_{Ji} \sin \phi_i, \quad (22)$$

where  $E_{J1} = E_{J2} = E_J$ . In the rotated coordinate we

obtain the relations

$$\begin{aligned} \frac{\eta}{\pi} \left[ n + f - \frac{3}{2\pi} \phi_c \right] &= \sin \phi_a \\ &= \lambda \sin(3\phi_c - 2\phi_a), \end{aligned} \quad (23)$$

where  $\lambda \equiv E_{J3}/E_J$  and we set  $\phi_b = 0$ . From Eqs. (18) and (23), we calculate  $\tilde{f} \equiv (1+\gamma)k_n l/2\pi$ . We calculate the values of the parameter  $\gamma$  to obtain  $\gamma \approx 200$  and  $\eta \approx 3300$  for the three-Josephson junction qubit of Ref. [5]. For  $\gamma \gg 1$ , the induced flux in Eq. (6) can be represented such that  $\Phi_{\text{ind}}/\Phi_0 = -\gamma k_n l/2\pi \approx -\tilde{f}$ .

In Fig. 5 the induced flux is shown when  $f = 0.45$  and  $\lambda = 0.8$ . The ground states in C and D induce a diamagnetic current while the ground states in A and B induce a paramagnetic current. In the inset of Fig. 5 we can see that  $f$  is very small for the qubit of Ref. [5] so that the induced flux is negligible and the boundary condition, Eq. (18), becomes  $2\pi n + 2\pi f = (\phi_1 + \phi_2 + \phi_3)$  which is used in Ref. [5]. On the contrary, when the value of  $\eta$  is much smaller, the induced flux become larger. The value of total flux approaches 0 ( $\Phi_0$ ) for diamagnetic (paramagnetic) current, which clearly shows the flux quantization condition. Thus we can see that the total flux becomes quantized as  $L_s E_J$  increases, while the fluxoid quantization condition, Eq. (3), is always satisfied. For superconducting ring without Josephson junction, the total flux is quantized when  $L_s$  is sufficiently large<sup>11</sup>.

#### IV. TUNNELING FREQUENCY

The quantum states in a cusp potential may be used to make a more efficient qubit because of high tunneling frequency across the barrier. This allows more single




FIG. 5: Induced diamagnetic (solid line) and paramagnetic (dashed line) fluxes as a function of  $\eta$  when  $f=0.45$ . Inset shows the induced diamagnetic flux for large  $\eta$ .




FIG. 6: Tunneling amplitude for (a) cusp barrier and (b) smooth barrier in the effective potential of rf-SQUID, where we set  $\alpha=64000$  (8000) and  $E_J=300\text{K}$  (75K) for the cusp (smooth) barrier. Figures (c) and (d) are for the three-Josephson junction qubit, where we set  $\alpha=64000$  (80) and  $E_J=300\text{K}$  (10K) for the cusp (smooth) barrier.

qubit operations in a short dephasing time. The geometric configuration of the cusp potential, such as its higher curvature and smaller width, causes higher tunneling frequency. We compare the tunneling rate calculated by the WKB approximation, the instanton method<sup>14</sup>, and the Fourier Grid Hamiltonian Method (FGHM)<sup>15</sup> in Fig. 6. The instanton method calculates the tunneling rate  $t$  as follows,

$$t = \hbar\omega_0 C_0 \sqrt{\frac{S_{\text{inst}}}{2\pi\hbar}} \exp\left[-\frac{S_{\text{inst}}}{\hbar}\right], \quad (24)$$

where  $S_{\text{inst}} = M \int_{-\infty}^{\infty} d\tau \dot{\phi}^2(\tau)$ ,  $M = (\Phi_0/2\pi)^2 C = \hbar^2/8E_c$ ,  $\omega_0 = \sqrt{k/M}$  is the frequency of small oscillation in a well with  $k = \partial^2 U_{\text{eff}}(\phi)/\partial\phi^2|_{\phi_{\text{min}}}$ , and  $C_0$  is a factor which depends on the shape of the double-well potential. The instanton action is evaluated in such a way that  $S_{\text{inst}} = \sqrt{2M} \int_{-\phi_{\text{min}}}^{\phi_{\text{min}}} \sqrt{U_{\text{eff}}(\phi)} d\phi$ , where  $-\phi_{\text{min}}$  and  $\phi_{\text{min}}$  represent two potential minima. The instanton satisfies the equation of motion  $(1/2)M\dot{\phi}^2(\tau) = U_{\text{eff}}[\phi(\tau)]$ . Integrating the equation of motion to obtain the instanton trajectory and comparing it with the asymptotic behavior,  $C_0$  is given by

$$C_0 = \phi_{\text{min}} \sqrt{\frac{2M\omega_0}{S_{\text{inst}}}} \exp[\omega_0 I], \quad (25)$$

where  $I$  is a constant obtained numerically.

The values of  $E_C$  are chosen through the parameter  $\alpha \equiv E_J/E_C$  which is roughly proportional to  $1/\eta$  in

experiments<sup>4,5,6</sup>. In Fig. 6 we see that the frequency of tunneling through the cusp barrier for low  $\eta$  is much higher than that for the smooth barrier in both rf-SQUID and the three-Josephson junction qubit. The tunneling through the potential barriers in the effective potential,  $U_{\text{eff}}$ , introduces the tunneling term in the single qubit Hamiltonian,

$$H_{\text{qubit}} = F(\Phi_{\text{ext}})\sigma^z - t\sigma^x, \quad (26)$$

where  $F(\Phi_{\text{ext}})$  is the energy level separation between two current states and  $\sigma^{z(x)}$  are the Pauli matrices. The first (second) term in Eq. (26) causes the single qubit rotation,  $R_z(R_x)$ . The operation time  $\tau_{\text{op}}$  for the  $R_x$  gate is inversely proportional to the tunneling frequency. Since the quality factor is  $Q_\phi = \tau_\phi/\tau_{\text{op}}$  with the dephasing time  $\tau_\phi$ , the present results show that the cusped barrier allows the quality factor that is an order of magnitude larger than occur with the smooth barrier.

Lower  $\eta$  requires higher  $E_J$  as shown in Eq. (16). Thus, a higher inductive flux in Fig. 5 could be detrimental to the phase coherence of the Cooper pair wave function. However, recent experiments for a three-Josephson junction loop with a Cooper-pair island<sup>16</sup> and a current-biased Josephson junction qubit<sup>17</sup> show that using a large Josephson junction the high quality factor can be achieved. A current-biased qubit of dc SQUID type with large Josephson junctions can be described by the present theory for low value of  $\eta$ .

The quantum phase slip may be relevant in a thin superconducting loop when the energy levels are degenerate<sup>10</sup>. The phase slip process causes the change of tunneling frequency and, thus, induces the decoherence. For the lower value of  $\eta$  in Eq. (16) the loop inductance is larger, which means the loop is thicker. Therefore the qubit using the cusp barrier with the lower value of  $\eta$  as shown in Fig. 2 may have a longer dephasing time than that using the smooth one.

## V. SUMMARY

Using the boundary condition for the phase evolution of the wave function of the Cooper pairs, we obtain a new double-well potential with cusp barriers for both rf-SQUID and three-Josephson junction loop. At the minimum of the effective potential we show that the current relation is satisfied. This picture allow us to calculate the wave vector of Cooper pairs,  $k_n$ , as a function of  $\eta$  and, thus, obtain the induced flux to show that the flux quantization condition is satisfied when the value of  $\eta$  becomes small. Moreover we calculate the tunneling frequency as a function of  $\eta$  which is the characteristic parameter responsible for the shape of the potential. The tunneling frequency in the cusp potential is much higher than that in the smooth potential, thus, the cusp potential offers a more efficient qubit.

## ACKNOWLEDGMENTS

This work is supported by the Korean Science and Engineering Foundation through the Center for Strongly

Correlated Materials Research (2002) at Seoul National University and the Brain Korea 21 Project in 2002.

- 
- <sup>1</sup> A. J. Leggett, S. Chakravarty, A. T. Dorsey, M. P. A. Fisher, A. Garg, and W. Zwerger, *Rev. Mod. Phys.* **59**, 1 (1987).
  - <sup>2</sup> A. J. Leggett, *Prog. Theor. Phys. Suppl. No.* **69**, 80 (1980); A. O. Caldeira and A. J. Leggett, *Ann. Phys. (N.Y.)* **149**, 374 (1983).
  - <sup>3</sup> J. Kurkijärvi, *Phys. Rev. B* **6**, 832 (1972); L. D. Jackel *et al.*, *ibid.* **9**, 115 (1974).
  - <sup>4</sup> R. Rouse, S. Han, and J. E. Lukens, *Phys. Rev. Lett.* **75**, 1614 (1995); J. R. Friedman, V. Patel, W. Chen, S. K. Tolpygo, and J. E. Lukens, *Nature* **406**, 43 (2000); S. Han, R. Rouse, and J. E. Lukens, *Phys. Rev. Lett.* **84**, 1300 (2000).
  - <sup>5</sup> J. E. Mooij, T. P. Orlando, L. Levitov, Lin Tian, Caspar H. van der Wal, and Seth Lloyd, *Science* **285**, 1036 (1999); T. P. Orlando, J. E. Mooij, Lin Tian, Caspar H. van der Wal, L. S. Levitov, Seth Lloyd, and J. J. Mazo, *Phys. Rev. B* **60**, 15398 (1999).
  - <sup>6</sup> Caspar H. van der Wal, A. C. J. ter Haar, F. K. Wilhelm, R. N. Schouten, C. J. P. M. Harmans, T. P. Orlando, Seth Lloyd, and J. E. Mooij, *Science* **290**, 773 (2000).
  - <sup>7</sup> M. A. Nielsen and I. L. Chuang, *Quantum Computation and Quantum Information* (Cambridge University, Cambridge, 2000).
  - <sup>8</sup> Y. Makhlin, G. Schön, and A. Shnirman, *Rev. Mod. Phys.* **73**, 357 (2001).
  - <sup>9</sup> M. Tinkham, *Introduction to Superconductivity* (McGraw-Hill, New York, 1996).
  - <sup>10</sup> K. A. Matveev, A. I. Larkin, and L. I. Glazman, *Phys. Rev. Lett.* **89**, 096802 (2002).
  - <sup>11</sup> Y. Imry, *Introduction to Mesoscopic Physics* (Oxford University, Oxford, 1997); L. Gunther and Y. Imry, *Solid State Commun.* **7**, 1391 (1969).
  - <sup>12</sup> F. Bloch, *Phys. Rev. B* **2**, 109 (1970).
  - <sup>13</sup> J. B. Majer, J. R. Butcher, and J. E. Mooij, *Appl. Phys. Lett.* **80**, 3638 (2002).
  - <sup>14</sup> U. Weiss, *Quantum Dissipative Systems* (World Scientific, Singapore, 1999).
  - <sup>15</sup> C. C. Marton and G. G. Balint-Kurti, *J. Chem. Phys.* **91**, 3571 (1989).
  - <sup>16</sup> D. Vion, A. Aassime, A. Cottet, P. Joyez, H. Pothier, C. Urbina, D. Esteve, and M. H. Devoret, *Science* **296**, 886 (2002).
  - <sup>17</sup> J. M. Martinis, S. Nam, J. Aumentado, and C. Urbina, *Phys. Rev. Lett.* **89**, 117901 (2002).